

## NH30ER

Call 800-321-7800 or visit us online at [www.nookindustries.com](http://www.nookindustries.com) to configure and order your NH30ER today!



| <b>Details</b>                   |       |
|----------------------------------|-------|
| Size [mm]                        | 30    |
| <b>Dimensions</b>                |       |
| L1 [mm]                          | 97    |
| L2 [mm]                          | 68    |
| L3 [mm]                          | 40    |
| L4 [mm]                          | 12    |
| M1 x l                           | M8X10 |
| H3 [mm]                          | 8     |
| W1 [mm]                          | 60    |
| W2 [mm]                          | 40    |
| W3 [mm]                          | 10    |
| <b>Forces and Torques</b>        |       |
| Basic Load Ratings C [kN]        | 28.24 |
| Basic Load Ratings C [lbf]       | 6347  |
| Basic Load Ratings C0 [kN]       | 46.87 |
| Basic Load Ratings C0 [lbf]      | 10535 |
| Static Moment Ratings-Ma [kN-m]  | 0.43  |
| Static Moment Ratings-Ma [lb-in] | 3819  |
| Static Moment Ratings-Mb [kN-m]  | 0.43  |
| Static Moment Ratings-Mb [lb-in] | 3819  |
| Static Moment Ratings-Mc [kN-m]  | 0.72  |
| Static Moment Ratings-Mc [lb-in] | 6336  |
| <b>Weight</b>                    |       |
| Weight-Block [kg]                | 0.99  |
| <b>Grease Fitting</b>            |       |
| Grease Fitting Part Number       | B-M6F |