


## PowerAC 1"-1 RA

Call 800-321-7800 or visit us online at [www.nookindustries.com](http://www.nookindustries.com) to configure and order your PowerAC 1"-1 RA today!



### Product Info

Screw Code	111-RA
Thread Direction	RH
Screw Material	4140 Series

### Details

Lead [in]	1.000
Starts	10
Pitch [in]	0.100
Turns Per Inch	1
Threads per Inch	10
Thread Code	111
Form	Stub
End Code for Types 1,2,3,5 [* Journals may show tracings of the thread]	20
End Code for Type 4 [* Journals may show tracings of the thread]	12

### Dimensions

A - Root Diameter Minimum [in]	0.906
D - Nominal Rod Diameter [in]	1.000

### Part Numbers

3 ft. Part Number	11111
6 ft. Part Number	12111
12 ft. Part Number	13111
20 ft. Part Number	

### Performance Specifications

Lead Accuracy +/- [in/in]	0.0003
---------------------------	--------

### Weight

Screw Weight [lb./ft.]	2.38
------------------------	------