

PowerAC 1"-6 RA

Call 800-321-7800 or visit us online at www.nookindustries.com to configure and order your PowerAC 1"-6 RA today!



Product Info	
Screw Code	106-RA
Thread Direction	RH
Screw Material	4140 Series
Details	
Lead [in]	0.167
Starts	1
Pitch [in]	0.167
Turns Per Inch	6
Threads per Inch	6
Thread Code	106
Form	2C
End Code for Types 1,2,3,5 [* Journals may show tracings of the thread]	17
End Code for Type 4 [* Journals may show tracings of the thread]	10
Dimensions	
A - Root Diameter Minimum [in]	0.786
D - Nominal Rod Diameter [in]	1.000
Part Numbers	
3 ft. Part Number	11106
6 ft. Part Number	12106
12 ft. Part Number	13106
20 ft. Part Number	
Performance Specifications	
Lead Accuracy +/- [in/in]	0.0003
Weight	
Screw Weight [lb./ft.]	2.16