

## PowerAC 1 3/4"-4 RA

Call 800-321-7800 or visit us online at [www.nookindustries.com](http://www.nookindustries.com) to configure and order your PowerAC 1 3/4"-4 RA today!



### Product Info

Screw Code	174-RA
Thread Direction	RH
Screw Material	4140 Series

### Details

Lead [in]	0.250
Starts	1
Pitch [in]	0.250
Turns Per Inch	4
Threads per Inch	4
Thread Code	174
Form	2C
End Code for Types 1,2,3,5 [* Journals may show tracings of the thread]	35
End Code for Type 4 [* Journals may show tracings of the thread]	19

### Dimensions

A - Root Diameter Minimum [in]	1.427
D - Nominal Rod Diameter [in]	1.750

### Part Numbers

3 ft. Part Number	11174
6 ft. Part Number	12174
12 ft. Part Number	13174
20 ft. Part Number	

### Performance Specifications

Lead Accuracy +/- [in/in]	0.0003
---------------------------	--------

### Weight

Screw Weight [lb./ft.]	6.97
------------------------	------