


PowerTrac 0631 - 0500 SRT RA, with SEL Ball Nut, Adjustable

Call 800-321-7800 or visit us online at www.nookindustries.com to configure and order your PowerTrac 0631 - 0500 SRT RA, with SEL Ball Nut,



Inch Ball Screw

Product Info

Screw Code	0631-0500 SRT RA
Precision	SRT
Screw Material	4150
Thread Direction	RH

Details

Ball Circle Diameter [in]	0.631
Lead [in]	0.500
Root Diameter [in]	0.500
End Code for Types 1,2,3,5 [* Journals may show tracings of the thread]	12
End Code for Type 4 [* Journals may show tracings of the thread]	8

Performance Specifications

Lead Accuracy +/- [in./ft.]	0.0040
-----------------------------	--------

Part Numbers

2 ft. Part Number	SRT6524
4 ft. Part Number	SRT6548
6 ft. Part Number	SRT6572
8 ft. Part Number	
12 ft. Part Number	
16 ft. Part Number	
20 ft. Part Number	

Weight

Screw Weight [lb./ft.]	0.82
------------------------	------

Inch Ball Nut, for SRT, Standard Accuracy, Preloaded, Adjustable, SEL

Product Info

Ball Nut Number	SEL10182
Thread Direction	RH

Details

Ball Circle Diameter [in]	0.631
Lead [in]	0.500
Nominal Ball Diameter [in]	0.125
Root diameter [in]	0.500

Forces and Torques

Torque to Raise 1 lb. [in-lb]	0.088
-------------------------------	-------

Flange Part Numbers

Flange Part Number	FLG7570
--------------------	---------

Wiper Part Numbers

Wiper Kit Part Number	-
-----------------------	---

Weight

Nut Weight [lb]	0.65
-----------------	------

Performance Specifications

Lead Accuracy +/- [in./ft.]	0.004
Maximum Adjustable Preload [lb]	288
Spring Rate x 10 ⁶ [lb./in.]	
Dynamic Load [lb]	960
Static Load [lb]	5565